

Leistungsdiagramm

Drehzahl [1/min]	Leistung [kW]							Drehmoment [Nm]
	1. Gang	2. Gang	3. Gang	4. Gang	5. Gang	6. Gang	Durchschnitt	
2.000	5,34						5,34	25,51
2.500	8,72	8,25					8,48	32,40
3.000	10,87	11,46	11,73				11,35	36,14
3.500	13,18	13,96	14,40	13,91		14,63	14,01	38,24
4.000	15,70	19,02	16,24	16,72		16,98	16,93	40,42
4.500	18,55	17,38	20,44	19,36		19,82	19,11	40,55
5.000	20,27	22,20	21,09	20,91		21,60	21,21	40,52
5.500	23,53	21,47	21,31	23,13		23,20	22,53	39,12
6.000	25,10	25,47	23,46	23,39	21,25	23,87	23,76	37,81
6.500	24,89	22,96	23,50	25,85	23,99		24,24	35,61
7.000	24,01	25,41	26,21	26,53	27,58		25,95	35,40
7.500	24,86	26,68	28,95	28,54	27,99		27,40	34,89
8.000	28,94	29,43	30,01	32,60	26,64		29,53	35,24
8.500	26,41	32,44	30,63	27,69			29,29	32,91
9.000	30,01	30,83	33,47				31,44	33,35
9.500	29,61	30,07	32,44				30,71	30,87
10.000	29,47	32,53	26,76				29,59	28,25
10.500	29,53	30,63					30,08	27,36
11.000	23,59						23,59	20,48

